

TAURUSTM

MULTI

HWT-301

Digital Harmonics Clamp Tester

AC Leakage Current ,400mA/4A/40A/300A
True rms reading, 40mm ϕ CT
Harmonics Current & Voltage



Features

- Harmonics and leakage current measurements.
- Up to 25th harmonics current and voltage measurements.
- True rms reading for ACA and ACV.
- Data-hold and Auto power off function.
- Confirm to IEC safety requirements.



An ISO 9001 : 2008 Company

Specifications

Safety standard	: IEC 61010-1, IEC 61010-2-032 ,Installation Category II 600V or Category III 300V.
E.M.C. standard	: EN 61326.
Measuring method	: Dual slope integration mode
AC conversion	: Truerms responding
Display	: 3.5 digit LCD, max. reading of 3999
Input frequency	: 45Hz ~65Hz
Affection of magnetic field	: 3mA or less (at 100A nearby conductor)
Jaw opening capability	: 40mm ϕ
Over range indication	: "OL" mark on LCD
Low battery indication	: "Battery" mark on LCD
Data hold indication	: "DH" mark on LCD
Sampling	: 2 times/sec.
Withstanding voltage	: AC 3700V 1 minute max. (Between the core of CT and buter case)
Operating temperature	: 0 °C to 40 °C, 80%RH max. (Without condensation)
Storage temperature	: - 10°C to 60 °C, 70%RH max. (Without condensation)
Power supply	: 1.5V (AM-4,LR03 or AAA) \times 3
Power consumption	: 13mA
Auto power off	: Approx.20 minutes later after power on
Battery life	: Approx.50 hours continuous
Size	: 70(W) \times 223(H) \times 34(D)mm
Weight	: Approx.440g
Accessories	: Hard carrying case.....1 Instruction manual.....1 Batteries.....3

Crest factor : <3 (0 ~50% of range)

Accuracy (23 °C \pm 5°C 80%RH or less) <2 (50 ~100% of range)

Range	Resolution	Accuracy	Max.input
AC 400mA	0.1mA	$\pm 1.0\%$ rdg ± 8 dgt	AC 300Arms
AC 4A	1mA		
AC 40A	10mA		
AC 300A	100mA	$\pm 1.0\%$ rdg $\pm 1\%$ of full scale	AC 250Vrms AC 450Vrms AC 400Vrms
AC 400mV	0.1mV	$\pm 1.0\%$ rdg ± 8 dgt	
AC 400V	100mV	$\pm 1.0\%$ rdg ± 8 dgt	
4000 Ω	1 Ω	$\pm 1.0\%$ rdg ± 8 dgt	AC 400Vrms

Harmonics mode

Measuring method	: Synchronous filter
Measurable harmonics	: Fundamental to 25 th harmonics
Minimum input	: More than 5% of full scale in each range

Harmonics	Accuracy(In case of more than 4 % harmonics is included against fundamental input)
1~9 th	($\pm 1\%$ rdg ± 5 dgt) \pm (basic accuracy of ACA or ACV) – (Error by neighboring harmonics)
10~19 th	($\pm 2\%$ rdg ± 5 dgt) \pm (basic accuracy of ACA or ACV) – (Error by neighboring harmonics)
20~25 th	($\pm 5\%$ rdg ± 5 dgt) \pm (basic accuracy of ACA or ACV) – (Error by neighboring harmonics)



TAURUS POWERTRONICS PVT LIMITED

Corporate Office : No. 26, "Mahadimane", 12th Main, 1st Block, Rajajinagar, Bangalore - 560 010.

INDIA. Tel : + 91 80 23012301 Fax : 91 80 23327736 Email : info@tauruspowertronics.com

Sales & Service Office : No. 648/54, KLE College 2nd Block, Rajajinagar, Bangalore - 560 010.

INDIA Tel : + 91 80 2352 2136 / 74.

Delhi Office : No. 15A/15, Brahma Villa, East Patel Nagar, New Delhi-110008. Ph : 011-47292274

South Africa Office : 10 Banff Street, Blue Valley Golf Estate Centurion 0157. Tel : + 27 11 5120100 Fax : + 27 11 5120101
E - mail : info@taurus.co.za